

TOCCARE MULTI AND MINI FIRMWARE UPDATE LEADS

If the Toccare Multi Loop panel is fitted with the TD571E main pcb, the straight through 9 pin serial lead should be used (see below).



This is also the firmware upgrade lead use for the Toccare MiniOne – all versions.

If the Toccare Multi Loop panel has the TD571D main pcb, the correct firmware upgrade connections/ lead is shown below.

Connection for boards TD571D and previous:

Panel Side	Connection	PC side
7 Jumpered with 8		7 Jumpered with 8
4	Connection with	2
3	Connection with	3
1	Connection with	5



The loop cards for the Toccare Multi-loop require the below lead for upgrading the firmware.

